



The Visionis 3008 is a black weather-proof keypad/reader that is standalone, hardwired, and designed for access control. The keypad provides proximity entry for up to 1000 users. This keypad is standalone but it can also work with Wiegand protocol controllers.

Keep in mind, this keypad DOES NOT come with software and is standalone. If connected to a controller, the keypad would work based on the controller's software. The modern design and quality components provide for a great access control solution.

Features

- Ultra-low power consumption, standby current is less than 30mA.
- Wiegand 26 or Wiegand 34 input and output.
- Waterproof Rate: IP68, indoor or outdoor use.
- Backlight Keypad: Easy to operate at night.
- Doorbell interface: Support external wired doorbell.

Model No.	VIS-3008
Card Type	EM
Working Voltage	DC12V-24V
Reading Range	2~5cm (0.79~1.97in.)
Capacity	1000 Users
Protocol	Wiegand 26-34 (input and output)
Door Opening Time	0~99s
Standby Current	≤30mA
Lock Output Load	≤3A
Door Relay Time	0 ~ 99s (adjustable)
Short-circuit Protection Output Time	≤100μS
Operating Temperature	-40°C ~ 60°C (-40°F ~ 140°F)
Working Humidity	10%~90%
Dimensions	111Lx46Wx22H (mm) - 4.37Lx1.82Wx0.87H (in.)
Protection Level	IP68 - No ingress of dust; complete protection against contact (dust tight), and waterproof



Disclaimer: VISIONIS reserve the right to go ahead with any modifications of models or features or price without forewarning. All the information and specifications stated in this document are current at the time of publication. Attention: We are not responsible for the improper installation of this kit. If you are not handy with electrical equipment you should contact a professional electrician. You will also need to check with your local Fire authority to see if you need anything else to comply with local Fire Codes. We are not responsible for any damage or fees that can occur.



support@visionistech.com



www.visionistech.com



The VIS-MINI-CNTRL is a mini single door control panel that can work with any Wiegand 26~37 bits output reader. It uses Atmel microcontroller to assure stable performance, and it is equipped with an infrared remote control for easy operation. The VIS-MINI-CNTRL supports 1,000 users.

For better security the VIS-MINI-CNTRL needs to be installed inside the facility in a restricted area. This device becomes the brain of this standalone application and all the credentials are being stored on the device. No information is stored on the entry device itself. It is also recommended to put this controller in an enclosure for better protection.

If the Keypad/Card Reader (Entry Device) is tampered with, the door will remain locked. The mini controller is the one controlling and securing your locking device.

The VIS-MINI-CNTRL provides a more secure option to add additional security to all type of Standalone Access Control products.

Features

- User Capacity: 1,000. Support Master Card function
- Multi access modes: Card, Card or PIN, Card with PIN and multi Cards/PINs
- Can connect with any reader with Wiegand 26~37 bits output
- Can connect with any keypad reader with 4bits, 8bits (ASCII), or 10bits virtual number output

Model No.	VIS-MINI-CNTRL
User Capacity	1,000 (Common user: 989, Visitor user: 10, Authorized user: 1)
Operating Voltage	12V DC
Idle Current / Active Current	< 100mA / < 150mA
Wiring Connections	Relay output, exit button, Wiegand input
Relay	One (NO, NC, Common)
Adjustable Relay Output Time	0~99 Seconds (5 seconds default)
Lock Output Load	2 Amp Maximum
Wiegand Interface	Wiegand 26~44, 56, 58 bits
Operating Humidity	Indoor
Environment	0 ~ 90%RH
Physical	ABS Shell
Dimensions	L65 x W54 x H19 (mm) - L2.56 x W2.13 x H0.75 (in.)
Unit Weight / Shipping Weight	40g / 100g



Disclaimer: VISIONIS reserve the right to go ahead with any modifications of models or features or price without forewarning. All the information and specifications stated in this document are current at the time of publication. Attention: We are not responsible for the improper installation of this kit. If you are not handy with electrical equipment you should contact a professional electrician. You will also need to check with your local Fire authority to see if you need anything else to comply with local Fire Codes. We are not responsible for any damage or fees that can occur.



support@visionistech.com



www.visionistech.com